WISCONSIN WRD DISTRICT LIBRARY COPY

UNITED STATES

DEPARTMENT OF THE INTERIOR

GEOLOGICAL SURVEY

DIRECT SOLUTION ALGORITHM FOR THE

TWO DIMENSIONAL GROUND-WATER FLOW MODEL

Open-File Report 79-202

	•	

UNITED STATES

DEPARTMENT OF THE INTERIOR

GEOLOGICAL SURVEY

DIRECT SOLUTION ALGORITHM FOR THE

TWO DIMENSIONAL GROUND-WATER FLOW MODEL

By S.P. Larson

Open-File Report 79-202

Reston, Va

June, 1978

,			

TABLE OF CONTENTS

	Page
Abstract	1
Introduction	2
D4 Ordering	3
Estimating work ratios	6
Computer code	11
Non-linear terms	12
Extrapolation	12
Uniform time steps	14
Changes to input data	14
Storage requirements and computation time	17
Roundoff Error	18
Utility	19
Conclusions	20
References cited	21
Annendix	22



ILLUSTRATIONS

		Page
Figure 1.	D4 (alternating diagonal) ordering	
	for a 5-by-5 grid	4
Figure 2.	Structure of matrix [A] assuming D4	
	ordering	5
Figure 3.	Work ratio (f_{D4}) for various elongation	
	ratios using D4 ordering	7
Figure 4.	Number of iterations that represent	
	the same amount of work as direct solution	
	assuming D4 ordering	10

ABSTRACT

Alternating diagonal ordering of node points for a two-dimensional finite-difference model of ground-water flow can be used to produce a direct solution algorithm that is computationally more efficient than iterative methods for moderately sized grids. Comparisons with the strongly implicit procedure, line-succesive overrelaxation, and the iterative alternating direction implicit procedure indicate that a direct method using alternating diagonal ordering can be competitive for as many as 3,000 equations. A FORTRAN computer code is included that is compatible with the two-dimensional ground-water flow model developed by the U.S. Geological Survey. The performance characteristics, computer storage requirements, and input data requirements for the direct solution algorithm are also included.

INTRODUCTION

As the availability of large capacity, high speed computers increases, the utility of direct methods (Gaussian elimination) for solving the set of linear algebraic equations encountered in ground-water modeling also increases. Price and Coats (1974) analyzed the use of direct methods for solving matrix equations encountered in reservoir simulation problems. They argue that it is well known that the commonly used method for ordering equations (that is, numbering a finite-difference grid in the smallest dimension) is certainly not the most efficient one. They go on to discuss the advantages of various alternative methods for ordering equations, in particular, a method which they refer to as D4 or alternating diagonal ordering. Results indicate that for large grids, D4 ordering requires only one-fourth the computing time and one-third the storage of standard ordering for non-symmetric problems in two-dimensions.

D4 ORDERING

The purpose of D4 ordering is to construct a coefficient matrix such that during the elimination process, sparsity will be conserved. Sparsity refers to the relative number of non-zero elements in the matrix. Certain multiplications and divisions can be avoided if zero elements are encountered during elimination and thus, if the sparsity is maximized, the work required to complete the elimination can be minimized. Consider a 5-by-5 grid shown in figure 1 with the grid points numbered in D4 fashion. The coefficient matrix [A], resulting from finite-difference approximations for a two-dimensional ground-water flow model will have non-zero entries denoted by the X's in figure 2.

Note that the upper half of [A] is already in upper triangular form (no non-zero elements to the left of the main diagonal). Eliminating unknowns associated with equations in the upper half from the equations in the lower half, produces non-zero entries in the lower half of [A] shown by the circles in figure 2. Note that, 1) calculations are not required for zero entries during this elimination, and 2) the bandwidth of non-zero entries created in the lower half is such that elimination through the lower half requires less work than standard ordering. Although item 2) may not be obvious from figure 2, Price and Coats (1974) demonstrate that these characteristics can reduce the work (number of multiplications and divisions) required for elimination to almost $N^2/4$ for large square grids, where N is the number of equations. Standard ordering requires N^2 multiplications and divisions; thus D4 ordering may require only one-fourth as much work.

1	15	4	19	9
14	3	18	8	23
				l
2	17	7	22	12
16	6	21	11	25
5	20	10	24	13

Figure 1.--D4 (alternating diagonal) ordering for a 5-by-5 grid.




Figure 2.-- Structure of matrix [A] assuming D4 ordering. The X characters denote non-zero elements in the original matrix [A]. The O characters denote non-zero elements formed by eliminating the X characters from the equations in the lower half of the matrix.

Also, symmetric matrices require only one-half as much work as non-symmetric matrices (operations are necessary only to the right of the main diagonal). Thus, the work required using D4 ordering may approach $N^2/8$ or $IJ^3/8$ for large square grids, where I and J are the grid dimensions.

ESTIMATING WORK RATIOS

For direct solution methods, the bandwidth of the coefficient matrix is an important characteristic because the storage requirements are proportional to the bandwidth and work is proportional to the square of the bandwidth. The work required for elimination of a banded symmetric matrix, using standard ordering, is approximately NJ²/2 or IJ³/2 where J, the smallest grid dimension, is assumed to approximate the bandwidth of the matrix. If the reduction in work produced by D4 ordering can be estimated, the work ratio between D4 ordering and iterative methods can also be estimated for various grid sizes.

If J<I, the bandwidth for standard ordering is J+1 and the work for large I and J is, as mentioned above, approximately $IJ^3/2$. Therefore:

$$W_{D4} \simeq f_{D4} \frac{IJ^3}{2} \tag{1}$$

where f_{D4} is the work ratio of D4 compared to standard ordering. Figure 3 shows work ratios of D4 to standard ordering (f_{D4}) achieved using an IBM 370/155 computer for various grid sizes and grid elongations (ratios of J to I). The Gauss-Doolittle method of decomposition (Forsythe and Moler, 1967) was used for both D4 and standard ordering. Thus an estimate of work using D4 ordering can be obtained using figure 3 and equation 1.




Figure 3.--Work ratio (f_{D4}) for various elongation ratios using D4 ordering.

For iterative solution methods, the work for each iteration is directly proportional to the number of equations and the total work required for a solution can be written:

$$W_{it} \simeq C_{i}N_{i}IJ \tag{2}$$

where C_1 is the number of multiplications and divisons required per iteration, N_1 is the number of iterations required for a solution, and IJ is the product of the grid dimensions which presumably approximates the number of unknowns for a given problem. The coefficient C_1 is about 31 for SIP (strongly implicit procedure), 47 for IADI (iterative alternating direction implicit procedure) and 23 for LSØR (line-successive overrelaxation) as coded in the model for two-dimensional groundwater flow developed by Trescott and others (1976). Note that the grid dimensions of the two-dimensional ground-water flow model are not exactly equal to I and J as discussed herein. To simplify computations, the model grid includes a border of inactive node points. Thus the model grid dimensions must be reduced by 2 to obtain the values of I and J used in this discussion.

The relative work between the D4 method and the iterative methods can be estimated by combining equations 1 and 2 as:

$$\frac{W_{D4}}{W_{it}} \simeq \frac{0.5f_{D4}J^2}{C_iN_i} \tag{3}$$

In developing a computer code that would be compatible with the two-dimensional ground-water flow model (Trescott and others, 1976), a small amount of overhead was required to calculate the coefficient matrix. To make a more accurate practical estimate of work ratios $(W_{\rm D4}/W_{\rm it})$, this overhead (approximately 20IJ multiplications) is included even though it becomes insignificant for large grids. The work ratio between D4 ordering and iterative methods can thus be approximated by:

$$\frac{W_{D4}}{W_{it}} \simeq \frac{0.5f_{D4}J^2 + 20}{C_iN_i}$$
 (4)

Figure 4 depicts the quantity $W_{\mathrm{D4}} N_{\mathrm{i}} / W_{\mathrm{it}}$ for various grid sizes (assuming I=J) for the three iterative methods included in the two-dimensional ground-water flow model. Equation 4 was used to construct the graph with values of f_{D4} obtained from figure 3 for a 1:1 elongation ratio. The quantity $W_{\mathrm{D4}} N_{\mathrm{i}} / W_{\mathrm{it}}$ is the number of iterations that yield the same amount of work required by direct solution with D4 ordering. Thus if an iterative method requires more than $W_{\mathrm{D4}} N_{\mathrm{i}} / W_{\mathrm{it}}$ iterations, the problem can be solved more efficiently using the D4 technique.




Figure 4.--Number of iterations that represent the same amount of work as direct solution; assuming D4 ordering.

It is also of interest to note that for a problem containing missing grid blocks (transmissivity equal to zero) or other irregularities in boundary geometry, the D4 technique may be more effective than equation 4 would predict. The reason is that missing grid blocks or irregular boundary geometry can result in a smaller bandwidth than that estimated from the grid dimensions. It is clear from equation 4 that if the bandwidth is reduced, the work required for the D4 technique may be significantly reduced because the work is directly proportional to the square of the bandwidth.

COMPUTER CODE

A FORTRAN computer code was developed to perform direct solution assuming D4 ordering. The code was constructed to be interchangeable with the SØLVE2 subroutine (LSØR) in the two-dimensional ground-water flow model (Trescott and others, 1976) and is listed in the appendix. Although the definition of some input data variables has changed, the only modification required to accommodate this subroutine into the program is to change one card in the main program. This card is also listed in the appendix. Before describing the changes in input data, a discussion of non-linear terms and uniform time steps is appropriate.

Non-linear Terms

For water-table aquifer systems; systems that include groundwater evapotranspiration; or combined water-table artesian simulations;
the resulting equations are non-linear or are only piecewise linear. The
term piecewise linear is meant to imply that the system is linear over certain
ranges of head but not uniformly linear over the entire range. To
analyze these problems effectively in the environment of a direct-solution
scheme, linearization techniques such as Newton-Raphson iteration (Blair and
Weinaug, 1969), or perturbation (J.V. Tracy, oral comm., 1977) can
be used. Although these methods solve the problem in a mathematically
pleasing fashion, a nonsymmetric coefficient matrix is produced, thus
significantly reducing the utility of a direct-solution scheme. For
most ground-water problems, a simple technique called extrapolation can give
satisfactory results with a minimum of computational effort.

Extrapolation

The purpose of using a technique such as perturbation is to avoid decomposing the coefficient matrix more than once per time step, as would be required if the non-linear terms were updated iteratively. A very simple, yet effective, method for obtaining an estimate of the non-linear terms is to extrapolate the head using values calculated from preceding time steps (Von Rosenberg, 1969). Generally, extrapolation is made to the mid-point of the next time step, thus providing estimates of the average non-linear coefficients during that step. If the point of extrapolation is variable, the scheme could be written as

$$h^* = h_{k-1} + \theta(h_{k-1} - h_{k-2})$$
 (5)

where h* is the estimated head to be used for calculating non-linear terms, h_{k-1} and h_{k-2} are heads at the k-1 and k-2 time levels, respectively, and θ is the extrapolation factor. If θ is set to zero, the scheme becomes one of explicit evaluation of non-linear terms at time level k-1. Although the method is simple in concept, it appears to be quite effective for many non-linear ground-water flow problems and yields an estimate of the solution to the non-linear problem in a single decomposition of the coefficient matrix.

Extrapolation may not eliminate all of the difficulties associated with non-linear terms, however, and so the computer code was structured to allow a sequence of "controlled" iterations during each time step. This takes the form of specifying a minimum number of iterations that must be completed during the step. Non-linear terms are evaluated using the head computed by the most recent iteration. A maximum number of iterations is also specified and the sequence is terminated if the maximum head change for an iteration is smaller than a specified tolerance. Termination of the sequence must be achieved within the maximum limit of iterations or the program will abort. However, by selecting an arbitrarily large closure tolerance, a minimum number of iterations can be guaranteed and the closure tolerance will be satisfied; thus the program will not The use of iteration, although somewhat inefficient computationally, should allow the solution of many problems that cannot be solved using only extrapolation.

Uniform Time Steps

For linear problems (artesian simulations with no evapotranspiration), a direct-solution technique can be very effective for simulations with uniform time steps. For these problems, the coefficient matrix does not change from one time step to the next and therefore only a single decomposition of the matrix is required. Heads at subsequent time steps are determined by reformulating the right hand sides of the difference equations and back substituting. The computational work required to reformulate and back substitute can be substantially less than that of decomposition, thus solving for several uniform time steps can be accomplished much more efficiently than an equivalent number of non-uniform steps.

The computer code is designed to take advantage of this reduction in work automatically if the necessary conditions exist. The necessary conditions are: 1) artesian simulation, 2) no evapotranspiration, 3) no iteration specified (see variable LENGTH below), and 4) uniform time steps.

Changes to Input Data

Subsequent paragraphs describe changes in the definitions of some input data variables used in the two-dimensional ground-water flow model (Trescott and others, 1976). Complete descriptions of the input data cards can be found on pages 49-55 of that report.

In group II, card 2, columns 21-30, the variable ERR is used to define the error criterion for closure on the iteration sequence for non-linear problems. If the calculated head change for an iteration is smaller than this value at all nodes, iteration will stop. Reasonable values of this parameter are probably about 0.1 or 0.2 and are related to the amount of error in transmissivity, evapotranspiration coefficients, or leakage coefficients that is acceptable. A large value of ERR can be used to guarantee closure after a minimum number of iterations has been completed.

In group II, card 2, columns 71-80, the variable LENGTH is defined as the minimum number of iterations desired. Thus if at least 2 iterations (in addition to the first decomposition) are desired, code 2 for LENGTH.

The maximum number of iterations desired is controlled by the parameter ITMAX (group I, card 4, columns 31-40). Set ITMAX to the maximum number of iterations desired. For some problems in which non-linearity is caused by the constraints on evapotraspiration coefficients or leakage coefficients in combined water-table artesian simulations, it may be desirable to iterate one or two times. If these two parameters (LENGTH and ITMAX) are set equal, and ERR is sufficiently large, LENGTH iterations will result. The purpose of this type of iteration is to insure that the water-level has not exceeded the allowable range for correct coefficient calculation during the time step. For example, evapotranspiration rate is limited to a maximum value if the water level is above land surface.

If the water level moves above land surface during a time step, the rate will be incorrect unless iteration is performed. However, this not be necessary for most problems and may only be significant for steady-state calculations. To avoid iteration, set LENGTH to zero.

In group II, card 3, columns 1-10, the variable HMAX is defined as a dampening factor similar to β ' used in the SIP algorithmn. It can be used to control oscillations for some highly non-linear water-table problems. (See Trescott and others, 1976, pp. 26-29).

Recall that the computer code was constructed as a replacement for subroutine $S\emptyset LVE2$ ($LS\emptyset R$) and thus $LS\emptyset R$ must be selected in group I, card 3, columns 26-30 to designate direct solution. If direct solution is selected, an additional data card is required prior to the group IV data. The card inputs the variable THETA used for extrapolation in water-table simulations. The format is F10.0 (columns 1-10) and a blank card is required for simulations in which direct solution is selected and THETA is not used (non-water-table simulations).

Additional arrays (AU, AL, IC, B, and IN) are required for direct solution and are dimensioned explicitly in the subroutine. (See Appendix). The required dimensions for AU, AL, IC, B, and IN are computed by the program and displayed on the program output. These variables and must be dimensioned at least as large as indicated on the output if the program is to run successfully. Array IN should always be dimensioned by at least DIML-2 by DIMW-2 (DIML and DIMW are the model grid dimensions). Initially, the other arrays can be dimensioned as follows, assuming N \simeq DIML x DIMW, AU and IC should be N/2 by 5, AL should be N/2 by DIML-1, and B should be N. If these

estimates differ significantly from the computed values, it may be appropriate to recompile using the computed dimensions.

Storage Requirements and Computation Time

Although storage requirements and computation time will depend entirely upon the type of computer system available, experience on an IBM $370/155 \frac{1}{}$ will be presented to provide some insight into expected values.

The core storage in thousand- byte units (1 byte = 8 bits, 32 bit words) can be approximated by:

$$C \simeq 87 + 0.034 \text{ N}^{1.23}$$
 (6)

where N is the number of active nodes (unknowns). This assumes that all options have been selected and that the Y array (see Trescott and others, 1976, p. 38) and the additional arrays required for D4 ordering are dimensioned exactly as required. Thus, for 1000 unknowns, 254K bytes of core storage are required. That part of this total required by the additional arrays in D4 is approximately;

$$C_{D4} \simeq \frac{7N + 0.5NB}{256}$$
 (7)

where B is one less than the smallest grid dimension (DIML-1 or DIMW-1). On modern computers, core storage is commonly available in quantities that allow serious consideration of problems involving as many as

 $[\]underline{1}$ / The use of brand name in this report is for identification purposes only and does not imply endorsement by the U.S. Geological Survey.

three thousand unknowns. As a practical matter, two-dimensional ground-water models seldom have more than 3,000 unknowns and therefore the D4 ordering technique should be an effective solution method.

An empirical relation for CPU (central processor) time in seconds, excluding data input, is:

$$t = (4.82 \times 10^{-5}) N^{1.69}$$
 (8)

This is the time required to complete an iteration, or a non-uniform time step, if iteration is unnecessary.

Roundoff Error

Roundoff error may cause difficulties for some problems if the magnitude of the elements of the coefficient matrix are highly variable. The decomposition of the matrix as written in the computer code in the appendix is carried out in single precision arithmetic and computers such as the IBM 370/155 that have a standard word size of 32 bits (6 to 7 decimal digits) can be prone to roundoff error. Computers that have larger standard word sizes (such as the CDC 7600 with 60 bit words) seldom have roundoff error problems.

Errors in the mass balance computed by the ground-water model are indications of roundoff error. If the error is large (greater than about one percent), it may be necessary to 1) carry out the decomposition in

double precision arithmetic, 2) iterate on the residual of the difference equations, 3) use some form of scaling the coefficient matrix, or 4) use a computer that has a larger standard word size. Iteration on the residual is accomplished merely by forcing iteration (LENGTH>0). Scaling the coefficient matrix requires modification of the computer code and was found to be somewhat ineffective on a test problem that exhibited roundoff error difficulties.

Utility

It is anticipated that the D4 method will be most useful in the solution of steady-state problems. For the iterative methods (SIP, ADI, and LS ϕ R) solutions to steady-state problems generally require many iterations unless the initial estimates of aquifer head are close to the solution. This is uncommon, however, and thus the D4 method should be very effective.

For transient problems, the aquifer head at the old time level is normally very close to the values at the new (unknown) time level and iterative methods can be used to obtain a solution in a few iterations. Large time steps however, will probably result in a situation similar to steady-state problems in that many iterations may be required by iterative methods and the D4 method may be more effective. Also, as indicated previously, transient simulations of linear problems using many time steps of equal size may be accomplished very efficiently using the D4 method.

CONCLUSIONS

The size and speed of modern computers have increased utility of direct- solution techniques as applied to ground-water modeling problems. The D4 ordering scheme with Gauss-Doolittle decomposition is competitive with iterative methods, such as SIP, IADI and LSØR, for many problems. The problem of selecting iteration parameters, restrictions on coefficient variation, and slowly converging or possibly non-converging sequences of estimates are virtually eliminated if direct solution is used.

Work ratios between the D4 method and the iterative methods
can be estimated and an evaluation of the utility of the D4 method can
be made. On an IBM 370/155 computer, the two-dimensional ground-water model
can be programmed to solve for 3,000 unknowns in the same amount of CPU
time required for about 13 SIP iterations. Thus, direct solution
assuming D4 ordering can be an effective solution algorithmn for a wide
range of ground-water modeling problems.

REFERENCES CITED

- Blair, P.M. and Weinaug, C.F., 1969, Solution of two-phase flow problems using implicit difference equations: Soc. Petrol. Eng. Jour. Dec., 1969, p. 417-424.
- Forsythe, C. E., and Moler, C. B., 1967, Computer solution of linear algebraic systems: New Jersey, Prentice-Hall, 148 p.
- Price, H. S., and Coats, K. H., 1974, Direct methods in reservoir simulation: Soc. Petrol. Eng. Jour., June 1974, p. 295-308.
- Trescott, P. C., Pinder, G. F. and Larson, S. P., 1976, Finite-difference model for aquifer simulation in two dimensions with results of numerical experiments: U.S. Geol. Survey, Techniques of Water Resources Inv., book 7, Chap. Cl, 116 p.
- Von Rosenberg, D. U., 1969, Methods for the numerical solution of partial differential equations: New York, American Elsevier Publishing Company, Inc., 128 p.

APPENDIX

Changes to program code to use D4

- 1) Change card MAN1710 in the Main program to:
 43), Y(L(20)),Y,(L(22)),Y(L(21)),Y(L(18))
 Note that this is a continuation card and thus the first
 character (4) is in column 6.
- 2) Insert the subroutine listed on the following pages in place of SØLVE2.

```
SUBROUTINE SOLVE2(PHI,D1,D2,D3,KEEP,PHE,STRT,T,S,QRE,WELL,TL,
                                                                             D4
                                                                                    1
    1 SL.D14.D5.D6.D7.EELX.D8.DELY.D9.TEST3.TR.TC.GRNU.SY.TOP.RATE.M.
                                                                             D4
                                                                                    2
                                                                             04
    2 RIVER, BOTTOM)
                                                                                    3
                                                                             D4
     SPECIFICATIONS:
                                                                                   10
                                                                             D4
                                                                                   20
     REAL #APHI .F . RHO . CL . CR . CA . CB . AREA . DXB . DYA
                                                                                   30
     REAL *4KEEP.M.KEEFN
                                                                             D4
     INTEGER ROPOPLODINGO DINGO CHKO WATERO CONVETO EVAPOCHOKO PNCHO NUMO HEADO DA
                                                                                   40
                                                                             04
                                                                                   50
    1CCNTP, LEAK, RECH, STP, ADI
                                                                             D4
                                                                                   60
     DIMENSION PHI(1),
                                                 KEEP(1) + PHE(1) + STRT(1) + D4
                                                                                   70
                                                                             04
                                                                                   80
    1T(1) . S(1) , QRE(1) , WELL(1) , TL(1) , SL(1) ,
                                                   TEST3(1), TH(1), TC(1).
                                                                             D4
                                                                                   90
    2
            DELX(1)
                               DELY(1) .
    3GRND(1) + SY(1) + TCP(1) + RATE(1) + M(1) + RIVER(1) + BOTTOM(1)
                                                                             04
                                                                                  100
                                                                             D4
     DIMENSION AU(500,5), AL(500,31), IC(500,5), IN(50,50), P(1000)
                                                                                  110
                                                                             D4
                                                                                  120
                                                                             D4
                                                                                  130
     CCMMON /SARRAY/ VF4(11)+CHK(15)
     CCMMON /SPARAM/ WATER, CCNVRT, EVAP, CHCK, PNCH, NLM, HEAD, CONTR, FROR, LED4
                                                                                  140
    1AK.RFCH.SIP.U.SS.TT.TMIN.ETDIST.QET.HRR.TMAX.CDLT.HMAX.YDIM.WIDTH.D4
                                                                                  150
    2NLMS.LSCR.ADI.DELT.SUM.SUMP.SUBS.STORE.TEST.ETQB.ETQD.FACTX.FACTY.D4
                                                                                  160
    SIERR.KOUNT.IFINAL.NUMT.KT.KP.NPER.KTH.ITMAX.LENGTH.NNEL.NW.OIML.DID4
                                                                                  170
                                                                                  180
    4MW, JNC1.INO1, F.P.FU, IXX, JXX, IDK1, IDK2
                                                                             D4
     RETURN
                                                                             D4
                                                                                  190
                                  200
                                                                             04
                                                                                  210
******
                                                                             D4
                                                                                  550
     FINTRY ITERS
                                                                             D4
                                                                                  055
*****
                                                                             04
                                                                                  240
                                                                             D4
                                                                                  250
     READ 530. THETA
                                                                             D4
                                                                                  260
     IN=UINF-S
                                                                             D4
                                                                                  270
     S-WMI D=ML
******CCMPUTE FQUATION NUMBERS FOR D4 ORDERING
                                                                             D4
                                                                                  280
                                                                             D4
                                                                                  290
     NXP=[M+JM+]
                                                                             D4
                                                                                  300
     DC 10 I=1.IM
                                                                             04
     DC 10 J=1+JM
                                                                                  310
                                                                             D4
                                                                                  320
     N=I+J#DIML+1
                                                                             D4
     PFF(N)=STFT(N)
                                                                                  330
  10 IN (I * J) = 0
                                                                             D4
                                                                                  340
                                                                             D4
                                                                                  350
     k = 0
*****ORDER--LEFT TO RECHT. POTTOM TO TUP
                                                                             04
                                                                                  360
                                                                             04
                                                                                  370
     DC 20 T=1+NXP+2
                                                                             04
                                                                                  380
     DC 50 7=1.7W
                                                                             D4
                                                                                  390
     IK=I-J+1
     IF (TK.LT.1) GO TC 20
                                                                             D4
                                                                                  400
     IF (IK.GT.1M) GO TO 20
                                                                             D4
                                                                                  410
                                                                             D4
                                                                                  415
     N=JK+J#DTML+1
                                                                             04
                                                                                  420
     IF (T(N).LE.O..OR.S(N).LT.O.) GO TC 20
                                                                             D4
                                                                                  430
     K=K+1
     IN(IK*J)=K
                                                                             D4
                                                                                  440
                                                                             04
                                                                                  450
  20 CONTINUE
                                                                             D4
                                                                                  460
     ICR=K+1
                                                                             04
                                                                                  470
     DC 30 I=2,NXP,2
                                                                             D4
                                                                                  480
     DC 30 J=1,JM
                                                                             D4
                                                                                  490
     IK=I-J+1
     IF (TK.LT.1) GO TC 30
                                                                             D4
                                                                                  500
     IF (IK.GT.IM) GO TO 30
                                                                             D4
                                                                                  510
                                                                             D4
                                                                                  515
     N=IK+J#DIML+1
     IF (T(N) . I.E.O. . OR . S(N) . LT . O . ) GO TO 30
                                                                             D4
                                                                                  520
                                                                             D4
                                                                                  530
     K=K+1
                                                                             D4
                                                                                  540
     IN(IK \bullet J) = K
                                                                             D4
                                                                                  550
  30 CCNTINUE
```

*****COMPUTE RANDWIDTH AND DETERMINE CONNECTING EQUATION NUMBERS

D4

560

```
MN0=9999
                                                                                      570
                                                                                 D4
      0 = 0 \times M
                                                                                      580
                                                                                 D4
      DC 80 I=1, IM
                                                                                 D4
                                                                                      550
      MU.I=U OB OD
                                                                                 D4
                                                                                      600
      IF=IN(T+J)
                                                                                 D4
                                                                                      610
      IF (IR.EQ.O.OR.IR.GE.ICR) GO TO BO
                                                                                 D4
                                                                                      620
      JL = 1
                                                                                 04
                                                                                      630
C##
     LFFT
                                                                                 D4
                                                                                      641
      IF ((J-1).LT.1) @C TO 40
                                                                                 D4
                                                                                      650
      IF (IN(I.J-1).EG.C) GO TO 40
                                                                                 04
                                                                                      660
                                                                                      670
      JL=JH+1
                                                                                 D4
      IC(IR,JU)=IN(I,J-1)
                                                                                 D4
                                                                                      680
      MV = IN(T + J - I) - IR
                                                                                 D4
                                                                                      690
      MXO=MAXO(MM,MXO)
                                                                                 D4
                                                                                      700
      MNO=MINO(MM.MNO)
                                                                                 D4
                                                                                      710
C##
     APCVE
                                                                                 04
                                                                                      720
   40 IF ((I-1).LT.1) GC TO 50
                                                                                 04
                                                                                      730
      IF (IN(I-1,J).FO.C) GO TO 50
                                                                                      740
                                                                                 D4
      JL = JH+1
                                                                                 D4
                                                                                      750
      IC(IP*JU)=IN(I-1*JU)
                                                                                 D4
                                                                                      760
                                                                                 D4
                                                                                      770
      MV = IN(I-1+J) - IR
      MNO=MINO(MM,MNO)
                                                                                      780
                                                                                 D4
      MXO=MAXO(MM,MXO)
                                                                                 D4
                                                                                      790
C##
     PELOW
                                                                                      800
                                                                                 D4
   50 IF ((I+1).GT.IM) 60 TC 60
                                                                                 04
                                                                                      810
      TF (IN(I+1+J)+EQ.C) GC TO 60
                                                                                 04
                                                                                      820
      けーリリー1
                                                                                 D4
                                                                                      830
      TC(IR+JU)=[N(I+]+L)
                                                                                 D4
                                                                                      840
                                                                                      850
                                                                                 D4
      AI - (U, I+I)NI = MM
      MXO=MAXO(MM.MXO)
                                                                                 D4
                                                                                      860
      MNO=MINO(MM+MNU)
                                                                                 D4
                                                                                      870
C##
                                                                                      880
     FIGHT
                                                                                 D4
   60 IF ((J+1).GT.JUM) 60 TO 70
                                                                                 D4
                                                                                      890
      IF (IN(I+J+1)+EG.C) GC TO 70
                                                                                 D4
                                                                                      900
                                                                                      910
      JL=JH+1
                                                                                 D4
      IC(IR,JU)=IN(I,J+1)
                                                                                      920
                                                                                 04
                                                                                      930
      HI = (I + U + I) - IH
                                                                                 D4
      (OXM+MM) OXAM=OXM
                                                                                 04
                                                                                      940
      MNO=MINO(MM, MNO)
                                                                                 D4
                                                                                      950
   70 IC(IR+1)=JU
                                                                                 04
                                                                                      960
   80 OCNTINUE
                                                                                 D4
                                                                                      970
                                                                                      980
      IE=MXO-MNC+2
                                                                                 D4
      NEQ=K
                                                                                 D4
                                                                                      990
      ICR1=ICR-1
                                                                                 D4 1000
      IB1=IP-1
                                                                                 D4 1010
                                                                                 D4 1020
      LF1=NFQ-ICR1
      LH=NEG-ICR
                                                                                 D4 1030
                                                                                     1040
      WRITE (P.510) HMAX.LENGTH.ITMAX.THETA
                                                                                 D4
                                                                                 D4 1050
      WRITE (P,520) ICR1, LH1, IB1, ICR1, NEQ, IM, JM
                                                                                 D4 1060
      RETURN
C################
                                                                                 D4 1070
                                                                                 D4 1080
      ENTRY NEWITB
D4 1090
                                                                                 D4 1100
      KCUNT=0
                                                                                 D4 1110
      ITYPE=0
      IF (CDLT.EQ.1..ANC.KT.GT.1.AND.LENGTH.EQ.C.AND.EVAP.NE.CHK(6)) ITYD4 1120
     1PE=1
                                                                                 D4 1130
                                                                                 D4 1140
      IF (NATER.NE.CHK(2)) GO TO 100
      ITYPE=2
                                                                                 D4 1150
```

D4 1160

D4 1170

DC 90 I=1, IM

DC 90 J=1.JM

```
N= I+J#DIML+1
                                                                        04 1180
     IF (T(N).LE.O..OR.S(N).LT.).) GO TO 90
                                                                        D4 1190
     DEL TAH= (PHI (N)-PHF (N)) *COLT*THETA
                                                                        D4 1200
                                                                        D4 1210
     DELMAX=0.1*(PFI(N)-BOTTCM(N))
     IF (ABS(DELTAH).GT.DELMAX) DELTAH=DELTAH#CELMAX/ABS(DELTAH)
                                                                        D4 1220
     PHI(N)=PHI(N)+DELTAH
                                                                        D4 1230
  90 CONTINUE
                                                                        D4 1240
     CALL TRANS
                                                                        04 1250
100 PIGI=0.
                                                                        D4 1260
** LOAD MATRIX A AND VECTOR P FOR D4
                                                                        04 1270
     IF (JTYPE.EQ.1) GC TO 130
                                                                        D4 1280
     PC 110 I=1.ICR1
                                                                        D4 1290
     DC 110 U=1.5
                                                                        D4 1300
 110 AL (I,J)=0.
                                                                        D4 1310
                                                                        D4 1320
     DC 120 I=1,LH1
     DC 120 U=1.IB1
                                                                        D4 1330
                                                                        D4 1340
 120 \text{ AL}(T,J) = 0.
 130 DC 140 1=1.NEG
                                                                        D4 1350
 140 H(I)=0.
                                                                        D4 1360
                                                                        D4 1370
     DC 310 I=1.IM
     DC 310 J=1.JM
                                                                        D4 1380
     IF (1N(I,J).FG.0) GO TC 310
                                                                        D4 1390
                                                                        D4 1400
     TR=IN(I.J)
     N=T+1+DIML#J
                                                                        D4 1410
     NA=N-1
                                                                        D4 1420
                                                                        D4 1430
     NE=N+1
     NL=N-DIML
                                                                        D4 1440
     N'R=N+DIML
                                                                        D4 1450
     DXR=DF(X(J+1)
                                                                        D4 1460
     DYR=DFLY(I+1)
                                                                        D4 1470
     STRIN=STRI (N)
                                                                        D4 1480
                                                                        D4 1490
     KEEPN=KEEP(N)
     PHEN=PHI(N)
                                                                        D4 1500
                                                                        D4 1510
     IF (ITYPE.EQ.1) PHEN=PHE(N)
     D4 1530
     --- COMPUTE COEFFICIENTS---
                                                                        D4 1540
     IF (FVAP.NE.CHK(6)) GO TO 160
                                                                        D4 1550
                                                                        D4 1560
     --- COMPUTE EXPLICIT AND IMPLICIT PARTS OF ET RATE---
                                                                        D4 1570
     GENDN=GRND(N)
                                                                        D4 1575
     ETOP=0.
                                                                        04 1580
                                                                        D4 1590
     ETQD=0.0
                                                                        D4 1600
     JF (PHEN.LE.GENDN-ETDIST) GO TO 160
     IF (PHEN.GT.GRNDN) GO TO 150
                                                                        D4 1610
                                                                        D4 1620
     FTQE=QET/ETDIST
     FTQD=FTQH# (ETCIST-GRNDK)
                                                                        D4 1630
     GC TO 160
                                                                        D4 1640
                                                                        D4 1650
 150 FIGD=GET
                                                                        D4 1660
                                                                        D4 1670
     --- COMPUTE STORAGE TERM---
 160 IF (CONVRT.EG.CHK(7)) GC TO 170
                                                                        D4 1680
                                                                        D4 1690
     RHO=S(N)/CELT
                                                                        D4 1700
     IF (WATER.EQ.CHK(2)) RHC=SY(N)/DELT
                                                                        D4 1710
                                                                        D4 1720
                                                                        D4 1730
     --- COMPUTE STOPAGE COEFFICIENT FOR CONVERSION PROBLEM---
 170 SLRS=0.0
                                                                        D4 1740
                                                                        D4 1750
     TCPN=TOP(N)
     IF (KEEPN.GE.TOPN.AND.PHEN.GE.TOPN) GC TO 210
                                                                        D4 1760
                                                                        D4 1770
     IF (KEEPN.LT.TOPN.AND.PHEN.LT.TOPN) GC TO 200
```

```
IF (KEEPN-PHEN) 160,190,190
                                                                             D4 178
  160 SUBS=(SY(N)-S(N))/DELT*(KEEPN-TOPN)
                                                                             D4 179
                                                                             D4 180
      GC TO 210
                                                                             D4 181
  190 SURS=(S(N)-SY(N))/DELT*(KEEPN-TOPN)
  200 REDESY (N) / DELT
                                                                             D4 182
                                                                             D4 183
      055 UL 39
  210 RED=S(N)/DELT
                                                                             D4 184
  220 IF (LEAK. NE. OFK (9)) GC TO 240
                                                                             D4 185
                                                                             D4 186
C
C
      ---COMPUTE NET LEAKAGE TERM FOR CONVERSION SIMULATION---
                                                                             D4 187
      IF (PATE(N).FG.0..OR.M(N).EG.O.) GO TC 240
                                                                             D4 188
      HED1=AMAX1 (STRIN.TOPN)
                                                                             D4 189
      U=1.
                                                                             04 190
                                                                             D4 191
      rfb2=n.
                                                                             D4 192
      IF (PHEN.GE.TCPN) GC TC 230
                                                                             D4 193
      HFD2=TOPN
                                                                             D4 194
  230 SL(N)=RATE(N)/M(N)#(HIVER(N)-HED1)+TL(N)#(HED1-HED2-STRTN)
                                                                             D4 195
                                                                             D4 196
  240 CCNTINUE
                                                                             D4 197
C
      AFFA=CXE#CYB
                                                                             D4 198
                                                                             D4 199
      F=(RHO+TL(N)+L+ETCH)+AREA
C#####LCAD COFFFICIENTS INTO AU AND AL
                                                                             D4 200
                                                                             D4 201
      CL=(TR(NL))#DY9
      CR=(TR(N))*DYF
                                                                             D4 202
                                                                             D4 203
      CA = (TC(NA)) # DXB
      CF = (TC(N)) #DXF
                                                                             D4 204
                                                                             D4 205
      IF (TTYPF.EQ.1) GC TO 300
                                                                             D4 206
      IF (IR.GE.ICR) GC TC 290
                                                                             D4 207
      JL = 1
      IF ((J-1).LT.1) GC TO 250
                                                                             D4 208
      IF (IN(I.J-1).EQ.C) GO TO 250
                                                                             D4 2091
                                                                             D4 210
      JL=J1;+1
                                                                             D4 2111
      AL (IP, JL) =-CL
                                                                             D4 213(
  250 IF ((T-1).LT.1) @C TO 260
                                                                             D4 2141
      TF (IN(I-1,J).EQ.C) GO TO 260
      JL=JU+1
                                                                             D4 2151
      AL (IP, JU) =-C4
                                                                             D4 2161
                                                                             D4 2181
  260 IF ((I+1).GT.IM) 60 TO 270
                                                                             D4 2191
      IF (IN(I+1.J).EQ. ) GC TO 270
                                                                             D4 2201
      Jし=JU+1
                                                                             D4 2211
      AL (IR, JL) =-CR
                                                                             D4 2231
  270 IF ((J+1).GT.JLM) (60 TC 280
                                                                             D4 2241
      IF (IN(I,J+1).EQ.C) GO TO 280
                                                                             D4 225(
      JL=JH+1
                                                                             D4 226(
      AL (IR,JU) =-CR
  SEO E=E+CA+CB+CL+CH
                                                                             D4 227(
                                                                             D4 2280
      AL (IR,1)=E
      B(JR)=(RHC*KEEPN+SL(N)+GRE(N)+WELL(N)=ETQC+SUBS+TL(N)*STRTN1*AREA+D4 2290
     1CA*PHI(NA)+CB*PHI(NA)+CL*PHI(NL)+CR*PHI(Nh)-E*PHI(N)
                                                                             D4 2300
                                                                             D4 2310
      IF (T(N).GT.O.) GC TO 310
      AL (IR.1)=1.
                                                                             D4 2330
                                                                             D4 2340
      B(IR)=0.
                                                                             D4 2350
      GC TO 310
  290 IFR=IR-ICR1
                                                                             D4 2360
                                                                             D4 2370
      E=E+CA+CR+CL+CR
                                                                             D4 2380
      AL(IRR,1)=E
      B(IR) = (RHO*KEEPN+SL(N)+GRE(N)+WELL(N)-ETQC+SUBS+TL(N)*STRTN)*AREA+D4 2380
                                                                             D4 2390
     1CA*PHI(NA)+CB*PHI(NB)+CL*PHI(NL)+CR*PHI(NP)-E*PHI(N)
```

IF (T(N).GT.O.) GC TO 310

AL (IRR,1)=1.

D4 2400

D4 2420

```
H(IR)=0.
                                                                                  D4 2430
     GC TO 310
                                                                                  D4 2440
300 P(IR)=(RHC*KEEPN+SL(N)+GRE(N)+WELL(N)-FTGC+SUBS+TL(N)*STRTN\*AREA+D4 2450
    1CA#PHT(NA)+CB#PHT(NB)+CL#PHI(NL)+CR#PHT(NR)-(E+CK+CL+CA+CB)#PHI(N)D4 2460
                                                                                  D4 2470
     IF (T(N).GT.O.) GC TO 310
                                                                                  D4 2480
     H(IR)=0.
310 CONTINUE
                                                                                  D4 2490
     IF (TTYPE.EQ.1) OC TO 380
                                                                                  D4 2500
*****ELIMINATE TO FILE AL
                                                                                  D4 2510
     DC 340 I=1.ICF1
                                                                                  D4 2520
     Ju=IC([+1)
                                                                                  04 2530
                                                                                  D4 2535
     Cl=1./AL(I.1)
                                                                                  D4 2540
     CC 330 U=2.UU
                                                                                  D4 2550
     LF=IC(I+J)
                                                                                  D4 2560
     L=LF-ICH1
                                                                                  D4 2570
     C=AL(I.J) #C1
                                                                                  D4 2580
     DC 320 K=J,JJ
     KL=IC(I+K)-LR+1
                                                                                  D4 2590
                                                                                  D4 2600
     \Delta L (L_{\bullet}KL) = \Delta L (L_{\bullet}KL) - C + \Delta U (I_{\bullet}K)
320 CCNTINUE
                                                                                  D4 2610
                                                                                  D4 2620
     AL(1,J)=C
                                                                                  D4 2630
330 CONTINUE
                                                                                  D4 2640
340 CCNTINUE
#####FLININATE AL
                                                                                  D4 2650
     PC 370 I=1.LH
                                                                                  D4 2660
     IF=I+ICF1
                                                                                  D4 2670
                                                                                  D4 2680
     L = J
                                                                                  D4 2685
     C1=1./AL(I+1)
     DC 360 U=2.IP1
                                                                                  D4 2690
                                                                                  04 2700
     IF (AL(I,J).FG.O.) GO TC 360
                                                                                  D4 2710
                                                                                  D4 2730
     C=AL(I,U)#C1
                                                                                  D4 2740
     KL=0
     DC 350 K=J.IH1
                                                                                  D4 2750
                                                                                  D4 2760
     KL=KL+1
                                                                                  D4 2770
     IF (AL(I_9K)_8NE_8O_8) AL(L_9KL)=AL(L_9KL)-C*AL(I_9K)
                                                                                  D4 2780
350 CONTINHE
                                                                                  D4 2790
     AL(I,J)=C
360 CCNTINUE
                                                                                  D4 2800
                                                                                  D4 2810
370 CCNTINUE
**MODIFY RHS, UPPER HALF
                                                                                  D4 2820
                                                                                  D4 2830
360 DC 400 I=1.ICF1
                                                                                  D4 2840
     J_{c} = IC(I + 1)
                                                                                  D4 2850
     DC 390 J=2,JJ
                                                                                  D4 2860
     LH = IC(I * J)
                                                                                  D4 2870
     B(LR) = B(LR) - AU(I \neq L) + B(I)
390 CCNTTNUE
                                                                                  D4 2880
                                                                                  D4 2890
400 H(I) = H(I) / AU(I \cdot 1)
**MODIFY RHS, LUWER HALF
                                                                                  D4 2900
                                                                                  D4 2910
     DC 420 I=1.LH
                                                                                  D4 2920
     IF=I+ICF1
                                                                                  D4 2930
     LR=IR
                                                                                  D4 2940
     DC 410 J=2,IR1
                                                                                  D4 2950
     LF=LR+1
                                                                                  D4 2960
     IF (AL(I_{\bullet}J).NE_{\bullet}O_{\bullet}) B(LR)=B(LR)+AL(I_{\bullet}J)*B(IR)
                                                                                  D4 2970
410 CCNTINUE
420 B(IR) = B(IR) / 4L(I, I)
                                                                                  D4 2980
                                                                                  D4 2990
#####PACK SOLVE--LOWER HALF
                                                                                  D4 3000
     H(NEQ)=B(NEQ)/AL(NEG-ICR1,1)
                                                                                  D4 3010
     DC 440 I=1.LH
                                                                                  D4 3020
     K=NEO-I
```

```
KL=K-ICH1
                                                                             D4 3030
      1 = K
                                                                             D4 3040
      DC 430 J=2+IB1
                                                                             D4 3050
      L=L+1
                                                                             D4 3060
      IF (\Delta L(KL \bullet J) \bullet NE \bullet 0 \bullet) B(K) = B(K) = AL(KL \bullet J) *B(L)
                                                                             D4 3070
  430 CENTINUE
                                                                             04 3080
  440 CCNTTNUE
                                                                             D4 3090
C#####BACK SOLVE -- UPPER HALF
                                                                             04 3100
      DC 460 I=1.ICF1
                                                                             D4 3110
      K=ICR-I
                                                                             D4 3120
      Ju=10(K+1)
                                                                             D4 3130
      DC 450 J=2,JJ
                                                                             D4 3140
                                                                             D4 3150
      L=TC(K.J)
      B(K)=B(K)-AU(K+J)\cdot AB(L)
                                                                             D4 3160
  450 CONTINUE
                                                                             D4 3170
  460 CCNTINUE
                                                                             D4 3180
C#####CCMPUTE NEW PHI VALUES
                                                                             D4 3190
      DC 470 I=1.IV
                                                                             D4 3200
      DC 470 J=1,JM
                                                                             D4 3210
                                                                             04 3220
      IF (TN(I+J).EG.0) GC TC 470
      N=I+1+DIML#J
                                                                             D4 3230
                                                                             D4 3240
      IF (JTYPE.NE.1) PrE(N)=KEEP(N)
      L=IN(I,U)
                                                                             D4 3250
                                                                             D4 3260
      TCHK=ABS (B(L))
      IF (TCHK.GT.HIGI) RIGJ=TCHK
                                                                             04 3270
      PHI(N)=PHI(N)+HMAX+B(L)
                                                                             D4 3280
                                                                             D4 3290
  470 CONTINUE
C#####CHECK TERMINATION CONDITIONS
                                                                             04 3300
      TFST3(KCUNT+1)=BTGI
                                                                             D4 3310
                                                                             D4 3320
      IF (LENGTH.GT.O.NAD.WATEP.NE.CHK(2)) GO TC 490
      IF (WATER.NE.CHK(2)) RETURN
                                                                             D4 3330
      IF (KOUNT.GE.LENGTH.AND.BIGI.LE.ERR) HETURN
                                                                             D4 3340
      KCUNT=KOUNT+1
                                                                             D4 3350
      IF (KOUNT-LE-ITMAX) GO TO 480
                                                                             04 3360
      WRITE (F.500)
                                                                             D4 3370
                                                                             D4 3380
      CALL TRANS
      CALL TERMI
                                                                             D4 3390.
                                                                             D4 3400
      RETURN
  480 CALL TRANS
                                                                             D4 3410
      GC TO 100
                                                                             D4 3420
  490 IF (KOUNT.GE.LENGTH.AND.BIGI.LE.ERR) HETUEN
                                                                             D4 3430
      KCUNT=KOUNT+1
                                                                             D4 3440
      IF (KOUNT.LE.ITMAX) GO TO 100
                                                                             D4 3450
                                                                             D4 3460
      WRITE (P.500)
      CALL TERMI
                                                                             D4 3470
      RETURN
                                                                             D4 3480
C
                                                                             D4 3490
                                                                             D4 3500
  500 FCRMAT (*OEXCEEDED PERMITTED NUMBER OF ITERATIONS FOR NON-LINEAR SD4 3510
     10LUTION*/* *,63(***))
                                                                             04 3520
  510 FCRMAT (1H-,41X, "SOLUTION BY LDU FACTORIZATION ASSUMING D4 GROEFIND4 3530
     16',/,42x.50(1H_);//,61x,'BETA =',F5.2,//,45x,'ITERATIONS: MINIMUMD4 3540
                                                                             D4 3550
     2 =+,15,/,58X, MAXIMUM =+,15,/,60X, THETA =+,F5.2)
  520 FCRMAT (1H-+25X++44444WARNING44444MINIMUM DIMENSIONS FOR ARRAYS USD4 3560
     1EC BY THIS METHOD ARE AS FOLLOWS: 1,//.64x+1AU: 1,15,1 BY
                                                                    51,/,64D4 3570
     2X++AL:++I5++ EY++15+/+64X++IC:++I5++ BY 5++/+65X++BI++I5+
                                                                             D4 3580
     3/+64X++IN:++15++ EY++15)
                                                                             D4 3585
  530 FCRMAT (8F10.4)
                                                                             D4 3590
```

D4 3600-

END

11